

Copper electroplating technology for microvia filling

Mark Lefebvre

Shipley Company, Marlboro, MA, USA

George Allardyce

Shipley Europe Ltd, Coventry, UK

Masaru Seita

Shipley Far East Ltd, Omiya, Japan

Hideki Tsuchida

Shipley Far East Ltd, Omiya, Japan

Masaru Kusaka

Shipley Far East Ltd, Omiya, Japan

Shinjiro Hayashi

Shipley Far East Ltd, Omiya, Japan

Keywords

Electroplating, Microvias

Abstract

This paper describes a copper electroplating enabling technology for filling microvias. Driven by the need for faster, smaller and higher performance communication and electronic devices, sequential build up (SBU) technology has been adopted as a viable multilayer printed circuit manufacturing technology. Increased wiring density, reduced line widths, smaller through-holes and microvias are all attributes of these high density interconnect (HDI) packages. Filling the microvias with conductive material allows the use of stacked vias and via in pad designs. Other potential design attributes include thermal management enhancement and benefits for high frequency circuitry. Electrodeposited copper can be utilized for filling microvias and provides potential advantages over alternative via plugging techniques. The features, development, scale up and results of direct current (DC) and periodic pulse reverse (PPR) acid copper via filling processes, including chemistry and equipment, are described.

Introduction

The continuing trend of portability and increasing functionality of electronic devices has driven the miniaturization and increased wiring density of printed circuit boards (PCBs) (Nargi-Toth, 1999; Coombs, 1996). Conventional multilayer PCBs with through-hole interconnect vias are not really a practical solution to satisfy these density requirements. This has driven the introduction of alternative approaches for high density interconnects (HDI), for example, sequential build up (SBU) technologies incorporating microvias. A number of differing SBU/microvia technologies are employed, however, a common feature is the achievement of increased densification.

Utilizing conductive filled microvias enables yet further package densification by facilitating via in pad and stacked vias designs. Electrodeposited copper via filling offers several potential advantages over alternative via plugging techniques:

- solid copper via plugs are inherently reliable and have higher conductivity than organic or conductive pastes;
- gains are realized in manufacturing productivity as densification and electrical connectivity is established in one step;
- copper electroplating is a technology already well known and extensively used in PCB fabrication.

All of these features ultimately lead to higher reliability, lower cost circuit densification. A program was therefore embarked upon to develop copper electroplating as a viable via filling technique.

Copper via fill development

The program for copper via fill process development was initiated in the LeaRon Japan research labs in Omiya, Japan. Product development objectives focused on maximizing via filling while minimizing thickness variation across the substrate surface. Filling ratio, a quantifiable measure of via filling, was used to compare capability of candidate formulations and shown schematically in Figure 1.

Initial target performance was to obtain a filling ratio > 80 percent for via diameters from 80 to 120 μm on 50-80 μm deep laser ablated vias at a nominal 25 μm deposit thickness.

Copper electrolytes

It is apparent that for the achievement of via filling, the plating rate in the via trench should be higher than on the surface and as such the copper electrolyte characteristics would be of fundamental importance in creating such differential plating rates.

There are several general classes of electrolytes used for electrolytic copper deposition, defined by the predominant copper counter ion, including: cyanide, fluoroborate, pyrophosphate and sulfate based systems (Graham, 1971). Sulfate based systems are most commonly used in PCB manufacturing owing to their low cost, convenient operation, safety and ease of waste treatment (69th Guidebook and Directory Issue, 2001). Development of an electrodeposited via fill process was therefore focused on acid copper sulfate systems. The acid copper sulfate system typically consists of copper sulfate, sulfuric acid, chloride ions and proprietary organic additive(s).

Inorganic components

- Cupric (Cu^{2+}) ions,
- sulfuric acid, and
- chloride.

Copper sulfate is the initial source of copper ions in solution. The copper content in solution is maintained by a coulombic equilibrium set up between the cathode, where plating occurs, and the anode. The anode is typically made of the same metal as is being plated; in this case copper acts as an ion source.

Sulfuric acid contributes to the overall solution conductivity, reducing anode and cathode polarization.

Chloride ions work in conjunction with the carrier to reduce anode polarization and help to refine the deposit morphology. When consumable (copper) anodes are used, chloride ions aid anode corrosion, setting up a uniform and adherent anode film.

Organic components

Proprietary additives are used to further refine deposit characteristics. An acid copper sulfate system operated

This paper was presented at the Electronics Circuits World Convention 9, held in Cologne, 7th to 9th October 2002. This paper was originally published in the 2002 proceedings of ECWC.



Circuit World
29/2 [2003] 9-14


© MCB UP Limited
[ISSN 0305-6120]
[DOI: 10.1108/03056120310454943]

The Emerald Research Register for this journal is available at
<http://www.emeraldinsight.com/researchregisters>



The current issue and full text archive of this journal is available at
<http://www.emeraldinsight.com/0305-6120.htm>

Figure 1
Via filling ratio definition



without additives typically yields deposits with poor physical properties. Organic additives are employed to improve grain refinement, throwing power, leveling and brightening of the deposit. Generally, there are three basic types of additives used in acid copper plating (Dietz, 2000a, b; Loshkarev and Gorova, 1998):

- carriers,
- brighteners, and
- levelers.

Carriers, also referred to as suppressors, are typically large molecular weight polyoxy-alkyl type compounds. Carriers are adsorbed at the surface of the cathode and in concert with chloride ions act to suppress the plating rate.

Brighteners are typically small molecular weight sulfur containing compounds that increase the plating reaction by displacing adsorbed carrier. Brightener compounds may exist in several forms in electrolytic working baths. Figure 2 shows the effect of increasing amounts of brightener in a functional acid copper electrolyte.

Levelers are typically nitrogen bearing heterocyclic or non-heterocyclic aromatic compounds that act by displacing brightener species in high current density sites (protrusions). The plating rate in effect is suppressed at these protrusions.

Via fill mechanism

In direct current (DC) plating, the mechanism for accelerated via filling (i.e. bottom up filling) is largely due to the role of the organic additives. The brightener (accelerator) concentration effectively increases in the via as the surface area becomes smaller. This localized increase in brightener concentration results in accelerated deposition in the via compared to the surface (Moffat *et al.*, 2000). This acts in combination with a greater degree of surface suppression provided by semi-selective adsorption of carrier species thus acting to further differentiate respective localized plating rates (Andricacos *et al.*, 1998). This is shown in Figure 3. In order for this accelerated bottom up filling to occur, the additive package components must operate in balance with each other and be maintained within specific parameters.

Figure 2
Brightener polarization curves





Figure 3
Organic additives in via filling



Pulse periodic reverse plating (PPR) in combination with organic additives can also provide a route to the differential plating rates required for via filling. In DC plating, only current (or voltage) is controlled while with a pulse periodic reverse current wave form, three parameters can be varied independently: on time, off time and current density, resulting in more intimate control of deposition.

Additionally, different PPR waveforms can be chained together to form complex waveforms. These variables affect adsorption and desorption phenomena, allowing control of variables otherwise unavailable with conventional DC plating (Kalanty *et al.*, 1993; Milad and Lefebvre, 2000). A schematic of a DC and a simple PPR waveform is given in Figure 4.

Organic additive selection

During the development program, extensive screening was conducted of various classes and combinations of additives, carriers and levelers for via filling efficacy. Candidate materials were further optimized with inorganic chemistry component concentration. Test substrates included CO₂/UV laser ablated microvias from 80 to 130 μm diameter in RCC and LDPP dielectric materials from 50 to 80 μm thick.

This optimization was done in conjunction with rectification type resulting in distinct via fill products for use with DC and PPR waveforms.

Process parameters – chemical effects

During the development of the respective DC and PPR via fill systems, the effect of inorganic component concentration on via filling was determined. The following constituents were studied for their effect on via filling performance:

- Copper sulfate,
- sulfuric acid, and
- chloride.

Of these, the copper sulfate concentration was found to have the principal influence. The effect of copper concentration on filling ratio is shown in Figure 5.

Note the opposite effect of increased copper concentration on through-hole throwing power Figure 6.

Figure 4
Waveform options




Figure 5
Effect of copper sulfate concentration on via filling





Figure 6
Relation between copper sulfate concentration and through-hole throwing power



Process parameters – physical effects

Physical process parameters studied included:

- current density,
- agitation,
- plating thickness,
- temperature,
- rectification (DC and PPR) and waveform (PPR).

The major effects are described below.

Current density – The relationship between current density and filling ratio for a specific via type is shown in Figure 7. In general, the loss in filling ratio with increasing current density is more evident as via depth increases and is further degraded with the use of glass-reinforced dielectric. Loss of via filling may be manifested as low filling ratio and/or voids. In general, lower current density improves via filling capability.

Solution agitation – This was found to play a key role in copper via filling. Figure 8 compares the effect of air agitation with jet or impingement plating on via filling. As evident, jet plating significantly improves via fill capability and uniformity of via fill across the panel compared to air agitation alone.

Figure 7
Effect of current density on 100 µm diameter × 80 µm deep vias





Figure 8
Effect of agitation on filling uniformity



Plating thickness – The effect of copper thickness has a significant effect on via filling ratio. As via diameter is increased, more copper is required to maintain fill.

Optimized process parameters – Based on the aforementioned development program optimum process parameters were derived. These are given for DC and PPR via fill processes in Tables I and II.

Scale up

To further explore process capability, scale up was undertaken in pilot plant then production scale electroplating equipment and the following elements were studied and optimized:

- idle time,
- bath age,
- substrate effects,
- consistency and uniformity,
- reliability.

Idle time– This is simply the non-plating time, where no current is applied and no deposition occurs. It is known that idle time can be detrimental to plating performance in acid copper systems. It is also known that acid copper performance can degrade with age and usage (Taylor *et al.*, 1999).

Table I
DC via fill process parameters

Parameter	Target	Range
CuSO ₄ .5H ₂ O	200 g/l	190-210 g/l
H ₂ SO ₄	100 g/l	90-110 g/l
Cl	50 ppm	40-60 ppm
VF A	2.0 ml/l	1.5-2.5 ml/l
VF B	20 ml/l	15-30 ml/l
Current density	1.5 A/dm ²	1.0-2.0 A/dm ²
Temperature	23°C	22-25°C

Table II
PPR via fill process parameters

Parameter	Optimum	Range
CuSO ₄ .5H ₂ O	130 g/l	120-140 g/l
H ₂ SO ₄	190 g/l	180-200 g/l
Cl	50 ppm	40-60 ppm
VF PPR A	1.0 ml/l	0.5-1.5 ml/l
VF PPR B	5.0 ml/l	4.0-8.0 ml/l
Current density	2.0 A/dm ²	1.0-3.0 A/dm ²
Forward:reverse current	1.0:0.5 A	
Forward:reverse time	10:0.5 msec	
Temperature	20°C	18-23°C

In Figures 9 and 10, the effect of idle time and bath age seen initially on via filling performance is shown.

It was postulated that much of the degradation in performance due to idle and aging effects could be attributed to organic byproducts, primarily from the brightener, which accumulate in the bath. These byproducts are formed both chemically during idle time and electrochemically during deposition. Most byproducts are inert and do not affect plating performance, however, some brightener byproducts are known to be electrochemically active (Herty *et al.*, 1998a, b). To determine whether brightener byproduct was responsible for loss of via fill capability, extensive studies were conducted.

In Figure 11, a known electrochemically active brightener byproduct was added in increasing amounts to a new bath. As evident, filling ratio was significantly compromised as concentration increased.

Clearly, to maintain via fill performance, it would be necessary to manage and minimize the generation of byproduct. Previous research activities within the organization had established techniques that could scavenge such byproduct. This methodology was therefore investigated in the via fill process with very positive results.

Figures 12 and 13 provide the results of idle and running time on via fill when operated with byproduct scavenging methodology.

This clearly confirmed that byproduct species were indeed responsible for the loss of via filling capability. However, the scavenging technique was fully effective in preventing the degradation in performance.

Substrate influence

The ability to reliably and completely fill a via is dependent on several factors beyond via diameter and depth. It was determined that the condition of the substrate also has

Figure 9
Effect of bath age




Figure 10
Effect of idle time




Figure 11
Effect of brightener byproduct concentration




Figure 12
Effect of idle time using byproduct scavenger





Figure 13
Effect of bath age with byproduct scavenger



a significant effect on via fill ability. These factors include via profile, thickness and uniformity of electroless copper coverage, degree of surface oxidation, and dielectric material. Each of these factors was investigated and the findings are summarized as follows.

The via profiles shown in Figure 14 demonstrate a range of shapes that can be filled. The profiles on the left are harder to fill than those on the right.

The thickness, uniformity of coverage and age of the electroless copper influence copper via fill. Thin or discontinuous electroless copper will not fill as reliably as a thick uniform deposit. Generally, a uniform electroless copper thickness $> 0.3 \mu\text{m}$ is required for reliable filling.


Oxidation of the electroless copper can also adversely effect via fill. To demonstrate this, substrates were processed through electroless copper and annealed at 120°C for 5 h prior to via fill. After $5 \mu\text{m}$ of copper via fill electrodeposition, no characteristic bottom-up fill was seen. Storage time and environment also play a role in via fill ability. Panels stored in a non-humidity controlled environment for 3 weeks were shown to exhibit poor fill compared to identically processed panels with fresh electroless copper. Panels stored in a controlled environment for similar times lost via fill at a slower rate than the uncontrolled environment. These substrate effects are shown in Figure 15.

The dielectric material has an influence on via fill capability. Non-glass reinforced materials are generally easier to fill than glass reinforced materials. The presence of glass protrusions into the via can also have an adverse effect on electroless copper coverage. Figure 16 shows the effect of glass reinforcement after laser ablation and copper via fill.

Figure 14
Via profile effects



Figure 15
Bottom-up fill after $5 \mu\text{m}$ copper




II

Mark Lefebvre, George Allardyce,
Masaru Seita, Hideki Tsuchida,
Masaru Kusaka
and Shinjiro Hayashi
*Copper electroplating technology
for microvia filling*
Circuit World
29/2 [2003] 9–14

Figure 16

Effect of glass reinforcement after laser ablation (top) and copper via fill (bottom)



Reliability and physical properties

Copper filled vias exhibit excellent reliability. A solid plug of copper is inherently robust. Table III shows the interconnect reliability of plated through-holes and blind microvias from a production copper via fill process. Table IV summarizes the tensile and elongation values obtained with copper via fill as a function of current density.

Process capability

The through-hole throwing power from the DC and PPR via fill processes are given in Figure 17. At higher panel thickness and current density, the advantage in throwing power of the PPR over DC system is evident. Conversely, the trend is reversed at low current density and the DC system provides an advantage. At panel thicknesses more typical of SBU construction, there is little difference in through-hole throwing power between the two systems.

Substrates comprised of three unique test patterns were used to compare the surface Cu thickness distribution of the DC and PPR via fill systems for pattern plate operation. Results are shown graphically in Figure 18. Figure 19 compares the characteristic trace profile obtained from DC and PPR via fill processes. In general, better pattern surface distribution with a more desirable shape is obtained with the PPR via fill system.

The capability of the processes to fill vias of various shapes and dimensions is an ongoing activity in both laboratory and commercial scales. A “Via Fill Capability Map” which displays filling ratio as a function of via diameter and depth is given in Figure 20. This is for the DC

Figure 17

Copper via fill through hole throwing power




Figure 18

Comparison of DC and PPR on pattern surface distribution




Figure 19

Comparison of DC and PPR on pattern shape




Figure 20

DC via fill capability map

Layer thickness	Hole diameter									
	30µm	40µm	50µm	70µm	80µm	90µm	100µm	120µm	130µm	140µm
30µm										
35µm										
40µm										
45µm										
50µm										
60µm										
80µm										

Table III

Interconnect reliability

Solder float (288°C/5 cycle)	Hot oil (260°C/100 cycle)	Thermal cycle (-65°/125°C)
0/152 BVH 0/20 TH 0/20 TH	0/152 BVH 0/20 TH 0/20 TH	0/832 BVH 0/832 TH 0/832 TH

Table IV

Physical properties

Current density (A/dm ²)	Tensile strength (N/mm ²)	Elongation (per cent)
1	307.7	22.8
2	323.6	27.9
3	314.7	25.3

system which has seen a greater degree of commercial adoption. At present the DC via fill system is capable of filling a broader range of via dimensions than the PPR system.

Comparison of DC and PPR systems

The relative pros and cons of the DC and PPR via fill systems are given in Table V.

Table V

DC and PPR pros and cons

DC via fill

- **Pros**
 - More capable and consistent via fill
 - Conventional rectification
 - Ease of operation
- **Cons**
 - Lower PTH throwing power for thick panels
 - Poorer pattern plate surface distribution

PPR via fill

- **Pros**
 - Higher PTH throwing power for thick panels
 - Better pattern plate surface distribution and profile
 - Greater potential through waveform mediation
- **Cons**
 - Less capable via fill

For pattern plate via fill applications that include thick panels with plated through-holes, the PPR via fill system may be more appropriate. Conversely, for panel or pattern plate applications with tight feature distribution and no plated through-hole requirement (e.g. packaging application), the DC system may be more appropriate.

Plating cell design

A key element of the copper via fill process is the engineering design of the specialty plating cell. This has led to a plating cell design that incorporates specific elements to enhance via fill capability and uniformity with process consistency. A side view of the cell design is shown in Figure 21.

Conclusions

Novel and enabling copper electroplating DC and PPR via fill systems have been developed for reliable and consistent blind via filling.

Each system has distinct attributes and offers the end user the flexibility to select a via fill process best tailored for their application.

These processes are currently seeing commercial applications and it is anticipated that there will be substantial adoption of this technology to produce features such as those shown in Figure 22.

Figure 21

Side view of via fill plating cell





Figure 22

Examples of copper filled vias



References

- Andricacos, P., Uzoh, C., Dukovic, J.O., Horkans, J. and Diligianni, H. (1998), *IBM J. Res. Dev.*, Vol. 42, p. 567.
- Coombs, C.F. Jr. (1996), *Printed Circuits Handbook*, 4th ed., McGraw-Hill, New York.
- Dietz, K. (2000a), "Organic additives in copper plating baths (Part 1a)", *CircuitTree*.
- Dietz, K. (2000b), "Organic additives in copper plating baths (Part 2)", *CircuitTree*.
- Graham, A.K. (1971), *Electroplating Engineering Handbook*, Van Nostrand Reinhold Co.
- Herty, J.P., Pletcher, D. and Goodenough, M. (1998a), "The chemistry of the additives in an acid copper plating bath. Part II", *J. Electroanal. Chem.*, Vol. 338.
- Herty, J.P., Pletcher, D. and Goodenough, M. (1998b), "The chemistry of the additives in an acid copper plating bath. Part III", *J. Electroanal. Chem.*, Vol. 338.
- Kalanty, M.R., Gabe, D.R. and Goodenough, M.R. (1993), "Unipolar and bipolar pulsed current electrodeposition for PCB production", *J. Appl. Electrochem.*, Vol. L3.
- Loshkarev, Y.M. and Gorova, E.M. (1998), "The electrodeposition of copper in the presence of brightening and smoothing agents", *Protection Metals*, Vol. 34 No. 5.
- Milad, G. and Lefebvre, M. (2000), "Is periodic reverse the right copper plating for your PCB manufacturing?", *Proceedings of AESF SUR/FIN 2000 Meeting*, June 2000, Chicago, IL.
- Moffat, T.P., Bonevich, J.E., Huber, W.H., Stanishevsky, A., Kelly, D.R., Stafford, G.R. and Josell, D. (2000), "Superconformal electrodeposition of copper in 500-90 nm features", *J. Electrochem. Soc.*, Vol. 147 No. 12.
- Nargi-Toth, K. (1999), "High-density PCBs", *PC FAB*, Vol. 22 No. 1.
- Taylor, T., Ritzdorf, T., Lindberg, F., Carpenter, B. and Lefebvre, M. (1999), "Electrolyte composition monitoring for copper interconnect applications", *Proc. Electrochem. Soc.*, pp. 96-8.
- "Metal finishing" (2001), *69th Guidebook and Directory Issue*, Vol. 99(No. 1A).